

D8 CENTRAL STATION FORMAT

The following program changes (to default settings) are necessary to enable standard reporting format.

P70E number E	Primary telephone number.
P71E number E	Secondary telephone number.
P72E xxxx E	4 digit Client Code.
P75E 2E 3E 4E 7E 8E	Report tamper alarms only (leds 5 and 6 on).
P84E hours E	Time until first test call, in 2 hour steps.
P88E 1E 4E	Enable open/close reports for area 1 and strobe on kiss-off (leds 1 and 4 on).
or P88E 5E	Enable forced opening report (led 5 on).
P89E 1E 5E	Enable test calls and line monitoring (leds 1 and 5 on).

The following option may be needed to suit your Control Room.

P78E zone E zone E	Select zones NOT to report multiple alarms (leds off).
---------------------------	---

The D8 is defaulted to Contact ID.